





GRID COUPLING


SIZE	Torque	Max. RPM	BORE		ØA	ØB	C	G	L	M	Approx Weight Kg
			MIN.	MAX.							
FGFC - 01	52	5800	10	28	105	43	38	0.80	76.8	53	3
FGFC - 02	150	5000	12	36	120	55	38	0.80	76.8	53	4
FGFC - 03	435	4500	16	40	144	60	45	0.80	90.8	60	5
FGFC - 04	995	3500	16	55	172	85	51	0.80	102.8	60	9
FGFC - 06	1000	3300	16	55	190	84	51	0.80	102.8	80	11
FGFC - 07	1950	3100	16	60	197	95	57	0.80	114.8	80	10
FGFC - 08	2150	2600	25	75	222	115	64	0.80	128.8	80	20
FGFC - 09	6200	2300	25	90	254	140	70	0.80	140.8	81	27
FGFC - 10	9300	2000	25	105	276	160	89	0.80	178.8	81	43
FGFC - 11	9500	1900	38	100	295	153	102	1.60	205.6	129	54
FGFC - 13	13700	1800	50	120	324	185	101.5	1.60	204.6	148	63
FGFC - 14	14100	1600	50	120	336	180	101.5	1.60	204.6	148	72
FGFC - 15	19900	1400	50	142	375	220	114	1.60	229.6	148	104
FGFC - 17	28500	1200	50	162	425	250	127	1.60	255.6	148	140
FGFC - 20	51000	1200	75	155	432	236	140	3.20	283.2	180	225
FGFC - 22	67000	1100	85	170	492	260	152	3.20	308.2	180	310
FGFC - 25	68300	1000	110	185	686	286	178	3.20	359.2	210	408
FGFC - 26	68500	1000	135	210	781	324	203	3.20	409.2	210	545
FGFC - 27	90000	900	145	242	876	368	228	6	462	250	875
FGFC - 28	108000	800	155	265	1015	406	228	6	462	285	1570



SIZE - 01 TO 17



SIZE - 20 TO 22



SIZE- 25 TO 28